



MANUAL

**EM1060 - 12-in-1 Card reader USB 2.0**

[WWW.EMINENT-ONLINE.COM](http://WWW.EMINENT-ONLINE.COM)

# EM1060 - 12-in-1 Card reader USB 2.0



## Warnings and points of attention

Always have products repaired by qualified Eminent personnel!

## Table of contents

1.0 Introduction .....	2
1.1 Functions and features .....	2
1.2 Packing contents .....	3
2.0 Installation procedure .....	3
2.1 Installing the SIM Editor software .....	3
2.2 Installing the USB Card reader .....	3
3.0 Reading a SIM card .....	4
3.1 Functions of SIM Editor .....	4
3.2 Managing telephone numbers .....	4
3.3 Managing SMS messages .....	5
3.4 Making a backup .....	5
4.0 Frequently Asked Questions .....	5
5.0 Service and support .....	5
6.0 Warranty conditions .....	6
7.0 Declaration of Conformity .....	6

## 1.0 Introduction

Congratulations on your purchase of this high-quality Eminent product! This product has undergone extensive testing by Eminent's technical experts. Should you experience any problems with this product, you are covered by a five-year Eminent warranty. Please keep this manual and the receipt in a safe place.

*Register this product now on [www.eminent-online.com](http://www.eminent-online.com) and receive product updates!*

### 1.1 Functions and features

With the USB Card reader you can read and write all popular memory cards! The 12-in-1 Card reader allows you to connect your SIM telephone card as well. When using the enclosed SIM Card editing software, you can edit your phonebook and SMS messages and save it to your computer.

*The USB Card reader supports the following memory cards: Mini SD, Micro SD (T-Flash), Secure digital, Multimedia card, Multimedia card plus (MMC), RS-MMC (MMC Mobile), MMC card 4.0, RS-MMC4.0 (MMC Mobile 4.0), MMC micro, MS / MD Duo / MS PRO DUO, MS PRO DUO HD and SIM card.*

## 1.2 Packing contents

The following parts need to be present in the packing:

- EM1060, 12-in-1 Card reader USB 2.0
- USB extension cable
- CD-rom with drivers and manual
- Manual

## 2.0 Installation procedure

Follow the steps below to install the USB Card reader on your computer.

If you have Windows ME, 2000, XP, Vista or Windows 7 you don't have to install drivers on your computer to use the USB Card reader. These versions of Windows have built-in drivers for this product. Installation will occur automatically.

### 2.1 Installing the SIM Editor software

Drivers for the SIM card port will be installed automatically when installing the software.

1. Insert the supplied CD-rom in your computer's CD-rom player or DVD player.
2. The wizard will start automatically.
3. Select your language.
4. Click 'Next'.
5. Select 'Install Software'.
6. Click 'Next'.
7. Follow the installation steps as displayed on your screen to finish the installation.

*You can also start the wizard manually when the CD-rom does not start automatically. Go to 'Start', 'Run', type 'x:\wizard\wizard.exe' ('x' is the drive letter of your CD-rom station) and press enter.*

### 2.2 Installing the USB Card reader

1. Connect the USB Card reader to an available USB port on your computer. We recommend using a USB 2.0 port if your computer is equipped with USB2.0 ports.
2. Windows will recognize the USB Card reader automatically.
3. Gently, insert your memory or SIM card in the card reader.
4. You will now see an additional 'Removable Disc' in Windows Explorer.
5. You can view, change or remove the contents of the memory card by accessing the removable disc.


*Hint! If your USB Card reader does not fit into the USB port of your computer, you can use the enclosed extension cable.*

## 3.0 Reading a SIM card

The USB Card reader can also read out SIM cards, besides reading out memory cards. This allows you to maintain your telephone numbers and SMS Messages.

1. Put the SIM card carefully in the card reader.
2. Click 'Start'.
3. Select 'Programs' or 'All Programs'.
4. Select 'SIM Card Kits'.
5. Click 'SIM Editor' to start the program.
6. Click the 'Connect to SIM' button to access the data on the SIM card. If a PIN code is required, please fill in this PIN code.

### 3.1 Functions of SIM Editor



- (1) Connect to the SIM card.
- (2) Copy SIM card data to computer.
- (3) Import or Export data.
- (4) SIM card information.
- (5) Enable, disable or block SIM card.
- (6) Activate, Block or change PIN.
- (7) Add name and phone number.
- (8) Delete selected Phone number and name or SMS.
- (9) Phone Book.
- (10) SMS overview.

### 3.2 Managing telephone numbers

1. Click 'Phone Book' (nr. 9).
2. Click 'New' in the menu (nr. 7).
3. You can now add a name and phone number.

4. The name and phone number will be stored automatically.

### 3.3 Managing SMS messages

1. Click 'SMS' (nr. 10).
2. The SMS messages will be loaded and displayed on your screen.
3. Check a message and click 'Delete' (nr. 8) when you want to delete a SMS message.
4. Check a message and click (nr. 2) when you want to copy a SMS message to your computer.

### 3.4 Making a backup

The SIM card editor has a very useful backup function which you can use to easily save all the telephone numbers and SMS to your hard drive.

1. Click 'Phonebook' (nr. 9) if you want to backup phone numbers, or click 'SMS' if you want to backup SMS messages to your computer.
2. Click the 'Import/Export' button (nr. 3) en select 'Export'.
3. The phone numbers or SMS data will be saved in the 'Temp' directory of the Windows folder on the hard disk. You can also select another location if desired.

## 4.0 Frequently Asked Questions

**Q:** *The USB Card reader is not found automatically.*

**A 1:** Your computer probably has a conflict on the used USB port. Try to use another USB port instead.

**A 2:** We recommend you to upgrade the drivers of your USB ports when the answer above does not solve the problem. Please contact the manufacturer of your computer for this.

**Q:** *The size of the USB Card reader is a too large, therefore I can hardly use the other USB ports on my computer. How do I solve this?*

**A:** We recommend you to use the USB extension cable.

**Q:** *The SIM editor asks me to fill in the PIN code of my SIM card.*

**A 1:** The SIM card you are using probably needs a PIN code. This is the same code you are using when powering on your telephone.

**A 2:** When you get this message while there is no pin code installed on your SIM card, we recommend you to put the SIM card in the card reader again. The card might have been placed incorrect in the card reader.

## 5.0 Service and support

This users manual has been carefully written by Eminent's technical experts.

If you have problems installing or using the product, please fill out the support form at the website [www.eminent-online.com/support](http://www.eminent-online.com/support).

## 6.0 Warranty conditions

The five-year Eminent warranty applies for all Eminent products unless mentioned otherwise before or during the moment of purchase. When having bought a second-hand Eminent product the remaining period of warranty is measured from the moment of purchase by the product's first owner. The Eminent warranty applies to all Eminent products and parts indissolubly connected to and/or mounted on the main product. Power supply adapters, batteries, antennas and all other products not integrated in or directly connected to the main product and/or products of which, without reasonable doubt, can be assumed that wear and tear show a different pattern than the main product are not covered by the Eminent warranty. Products are not covered by the Eminent warranty when exposed to incorrect/improper use, external influences and/or when opened by parties other than Eminent.

## 7.0 Declaration of Conformity

To ensure your safety and compliance of the product with the directives and laws created by the European Commission you can obtain a copy of the Declaration of Conformity concerning your product by sending an e-mail message to: [info@eminent-online.com](mailto:info@eminent-online.com). You can also send a letter to

Eminent Computer Supplies  
P.O. Box 276  
6160 AG Geleen  
The Netherlands

Clearly state 'Declaration of Conformity' and the article code of the product of which you would like to obtain a copy of the Declaration of Conformity.



Trademarks: all brand names are trademarks and/or registered trademarks of their respective holders.

The information contained in this document has been created with the utmost care. No legal rights can be derived from these contents. Eminent cannot be held responsible, nor liable for the information contained in this document.



Eminent is a member of the Intronic Group